



d-COPIA

4513MF e 4514MF

ENVIRONMENTAL INFO

D-COPIA 4513MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	6,4 A
Power consumption (Max.)	1276 W
Power consumption (Printing)	630 W
Power consumption (sleep mode)	0,5 W
Power consumption (Ready mode)	50 W
Power consumption (Off mode)	0,08 W
TEC (Typical Electricity Consumption) kWh/week	2,2 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,6 W
Power consumption in networked stand-by - WiFi	Not measurable
Power consumption in networked stand-by - All networks	0,8 W
Networked stand-by mode switch time	1
Noise level in stand-by	40,6 dB(A) Lwad - RAL-UZ 205
Noise level in copying	68,4 dB(A) Lwad - RAL-UZ 205
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,23 mg/h RAL-UZ 205
Styrene emission	0,01 mg/h RAL-UZ 205
TVOC emission	4,14 mg/h RAL - UZ 205



D-COPIA 4514MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	6,4 A
Power consumption (Max.)	1276 W
Power consumption (Printing)	630 W
Power consumption (sleep mode)	0,5 W
Power consumption (Ready mode)	50 W
Power consumption (Off mode)	0,08 W
TEC (Typical Electricity Consumption) kWh/week	2,2 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,6 W
Power consumption in networked stand-by - WiFi	Not measurable
Power consumption in networked stand-by - Fax	0,5 W
Power consumption in networked stand-by - All networks	0,8 W
Networked stand-by mode switch time	1
Noise level in stand-by	40,6 dB(A) Lwad - RAL-UZ 205
Noise level in copying	68,4 dB(A) Lwad - RAL-UZ 205
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,29 mg/h RAL-UZ 205
Styrene emission	0,01 mg/h RAL-UZ 205
TVOC emission	4,14 mg/h RAL - UZ 205