



d-COPIA

4513MF **PLUS** 4514MF **PLUS** 5514MF 6014MF

ENVIRONMENTAL INFO

D-COPIA 4513MF PLUS

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	6,4 A
Power consumption (Max.)	1276 W
Power consumption (Printing)	630 W
Power consumption (sleep mode)	0,5 W
Power consumption (Ready mode)	50 W
Power consumption (Off mode)	0,08 W
TEC (Typical Electricity Consumption) kWh/week	2,4 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,6 W
Power consumption in networked stand-by - WiFi	Not measurable
Power consumption in networked stand-by - Fax	NA
All networks	0,8 W
Networked stand-by mode switch time	1
Noise level in stand-by	39,6 dB(A) Lwad - RAL-UZ 205
Noise level in copying	68,4 dB(A) Lwad - RAL-UZ 205
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,23 mg/h RAL-UZ 205
Styrene emission	0,01 mg/h RAL-UZ 205
TVOC emission	4,77 mg/h RAL - UZ 205

D-COPIA 4514MFPLUS

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	6.4 A
Power consumption (Max.)	1276 W
Power consumption (Printing)	630 W
Power consumption (sleep mode)	0,5 W
Power consumption (Ready mode)	50 W
Power consumption (Off mode)	0,08 W
TEC (Typical Electricity Consumption) kWh/week	2,4 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,6 W
Power consumption in networked stand-by - WiFi	Not measurable
Power consumption in networked stand-by - Fax	0,5 W
All networks	0,8 W
Networked stand-by mode switch time	1
Noise level in stand-by	39,6 dB(A) Lwad - RAL-UZ 205
Noise level in copying	68,4 dB(A) Lwad - RAL-UZ 205
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,23 mg/h RAL-UZ 205
Styrene emission	0,01 mg/h RAL-UZ 205
TVOC emission	4,77 mg/h RAL - UZ 205



D-COPIA 5514MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	7.0 A
Power consumption (Max.)	1271 W
Power consumption (Printing)	711 W
Power consumption (sleep mode)	0,5 W
Power consumption (Ready mode)	64 W
Power consumption (Off mode)	0,08 W
TEC (Typical Electricity Consumption) kWh/week	2,9 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,6 W
Power consumption in networked stand-by - WiFi	Not measurable
Power consumption in networked stand-by - Fax	0,5 W
All networks	0,8 W
Networked stand-by mode switch time	1
Noise level in stand-by	39,2 dB(A) Lwad - RAL-UZ 205
Noise level in copying	71,1 dB(A) Lwad - RAL-UZ 205
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,27 mg/h RAL-UZ 205
Styrene emission	0,06 mg/h RAL-UZ 205
TVOC emission	4,56 mg/h RAL - UZ 205



D-COPIA 6014MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	7.0 A
Power consumption (Max.)	1276 W
Power consumption (Printing)	723 W
Power consumption (sleep mode)	0,5 W
Power consumption (Ready mode)	64 W
Power consumption (Off mode)	0,08 W
TEC (Typical Electricity Consumption) kWh/week	3,1 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,6 W
Power consumption in networked stand-by - WiFi	Not measurable
Power consumption in networked stand-by - Fax	0,5 W
All networks	0,8 W
Networked stand-by mode switch time	1
Noise level in stand-by	40,1 dB(A) Lwad - RAL-UZ 205
Noise level in copying	71,6 dB(A) Lwad - RAL-UZ 205
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,27 mg/h RAL-UZ 205
Styrene emission	0,06 mg/h RAL-UZ 205
TVOC emission	4,56 mg/h RAL - UZ 205