

d-Copia

PG L2745, PG L2750, PG L2755

ENVIRONMENTAL INFO

PG L2745

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	5.6 A
Power consumption (Max.)	1,234 W
Power consumption (Printing)	606 W
Power consumption (sleep mode)	0.5 W
Power consumption (ready mode)	8.4 W
Power consumption (Off mode)	0.1 W
TEC (Typical Electricity Consumption) kWh/week	0.59
Power consumption in networked stand-by - Ethernet	0.6 W
Power consumption in networked stand-by - USB	0.6 W
Power consumption in networked stand-by -Wireless	not measurable
All networks	0.7 W
Networked stand-by mode switch time	1 min
Noise level in stand-by	50 dB(A) Lwad RAL-UZ 219
Noise level in copying	70.3 dB(A) Lwad RAL-UZ 219

Ozone emission	0.21 mg/h RAL-UZ 219
Benzene emission	inferiore ai limiti misurabili RAL-UZ 219
Fine dust emission	0.13 mg/h RAL-UZ 219
Styrene emission	0.12 mg/h RAL-UZ 219
TVOC emission	4.95 mg/h RAL-UZ 219

PG L2750

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	5.6 A
Power consumption (Max.)	1,247 W
Power consumption (Printing)	652 W
Power consumption (sleep mode)	0.5 W
Power consumption (ready mode)	9 W
Power consumption (Off mode)	0.1 W
TEC (Typical Electricity Consumption) kWh/week	0.67
Power consumption in networked stand-by - Ethernet	0.6 W
Power consumption in networked stand-by - USB	0.6 W
Power consumption in networked stand-by -Wireless	not measurable
All networks	0.7 W
Networked stand-by mode switch time	1 min
Noise level in stand-by	50.8 dB(A) Lwad RAL-UZ 219
Noise level in copying	70.1 dB(A) Lwad RAL-UZ 219
Ozone emission	0.21 mg/h RAL-UZ 219
Benzene emission	below detection limit RAL-UZ 219
Fine dust emission	below detection limit RAL-UZ 219
Styrene emission	0.08 mg/h RAL-UZ 219
TVOC emission	5.37 mg/h RAL-UZ 219

PG L2755

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	5.6 A
Power consumption (Max.)	1,251 W
Power consumption (Printing)	676 W
Power consumption (sleep mode)	0.5 W
Power consumption (ready mode)	9 W
Power consumption (Off mode)	0.1 W
TEC (Typical Electricity Consumption) kWh/week	0.73
Power consumption in networked stand-by - Ethernet	0.6 W
Power consumption in networked stand-by - USB	0.6 W
Power consumption in networked stand-by -Wireless	not measurable
All networks	0.7 W
Networked stand-by mode switch time	1 min
Noise level in stand-by	52.5 dB(A) Lwad RAL-UZ 219
Noise level in copying	71.2 dB(A) Lwad RAL-UZ 219
Ozone emission	0.21 mg/h RAL-UZ 219
Benzene emission	below detection limit RAL-UZ 219
Fine dust emission	below detection limit RAL-UZ 219
Styrene emission	0.08 mg/h RAL-UZ 219
TVOC emission	5.37 mg/h RAL-UZ 219



Olivetti S.p.A.
Strada Monte Navale, 2/c 10015 IVREA (TO) Italy
www.olivetti.com
Copyright © 2024 Olivetti

All rights reserved
The manufacturer reserves the right to make changes to the product described in this manual at any moment and without giving prior warning.
No part of this document may be copied, reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying, recording or other, without obtaining prior written authorisation from the publisher.